



KERN & Sohn GmbH

Ziegelei 1
D-72336 Balingen
E-Mail: info@kern-sohn.com

Tel: +49-[0]7433- 9933-0
Fax: +49-[0]7433-9933-149
Internet: www.kern-sohn.com

Operating instruction(EN)

Balíková kontrolná váha KERN ECE(SK)

Version 2.0
08/2011
GB



ECE-BA-e-1120



KERN ECE

Version 2.0 08/2011

Operating instruction

Platform scale

Table of contents:

1	Technical data	3
2	Fundamental information (general)	4
2.1	Intended use	4
2.2	Inappropriate use	4
2.3	Guarantee.....	4
2.4	Monitoring the test substances	5
3	Fundamental safety information	5
3.1	Observe the information in the operating instructions.....	5
3.2	Staff training	5
4	Transport and storage	5
4.1	Acceptance check	5
4.2	Packaging / return transport	5
5	Unpacking, installation and commissioning	6
5.1	Place of installation, place of use.....	6
5.2	Unpacking the Balance.....	6
5.2.1	Installation	6
5.2.2	Package volume	7
5.3	Mains supply/ Battery operation.....	7
5.3.1	Mains supply.....	7
5.3.2	Battery operation	7
5.4	Initial start-up.....	9
5.5	Adjustment.....	9
5.6	Adjusting	9
6	Operation	10
6.1	Weighing	10
6.2	Taring (TARE key)	10
7	Maintenance, upkeep, disposal	11
7.1	Cleaning	11
7.2	Maintenance, upkeep	11
7.3	Disposal.....	11
8	Troubleshooting	12

1 Technical data

KERN	ECE10K5	ECE20K10	ECE50K20
Readout (d)	5 g	10 g	20 g
Weighing range (max)	10 kg	20 kg	50 kg
Taring range (subtractive)	10 kg	20 kg	50 kg
Reproducibility	5 g	10 g	20 g
Linearity	± 10 g	± 20 g	± 400 g
Adjusting weight (not included), adjustment/ tolerance as per M3	5 kg (M3)	10 kg (M3)	20 kg (M3)
Stabilisation time (typical)	2 sec.		
Optimal temp. of operation	+ 5° C + 35° C		
Humidity	max. 80 % (non-condensing)		
Size (W x D x H) mm	320 x 300 x 60		
Weighing plate mm	320 x 260		
Weight kg (net)	1,7		

2 Fundamental information (general)

2.1 Intended use

The balance you have acquired serves to determine the weighing value of the material to be weighed. It is intended to be used as a “non-automatic” balance, i.e. the material to be weighed is manually and carefully placed in the centre of the weighing plate. The weighing value can be read off after a stable weighing value has been obtained.

2.2 Inappropriate use

Do not use the balance for dynamic weighing. In the event that small quantities are removed or added to the material to be weighed, incorrect weighing results can be displayed due to the “stability compensation” in the balance. (Example: Slowly draining fluids from a container on the balance.)

Do not leave a permanent load on the weighing plate. This can damage the measuring equipment.

Be sure to avoid impact shock and overloading the balance in excess of the prescribed maximum load rating (max.), minus any possible tare weight that is already present. This could cause damage to the balance.

Never operate the balance in hazardous locations. The series design is not explosion-proof.

Structural alterations may not be made to the balance. This can lead to incorrect weighing results, faults concerning safety regulations as well as to destruction of the balance.

The balance may only be used in compliance with the described guidelines. Varying areas of application/planned use must be approved by KERN in writing.

2.3 Guarantee

The guarantee is not valid following

- non-observation of our guidelines in the operating instructions
- use outside the described applications
- alteration to or opening of the device
- mechanical damage and damage caused by media, liquids
- natural wear and tear
- inappropriate erection or electric installation
- overloading of the measuring equipment

2.4 Monitoring the test substances

The metrology features of the balance and any possible available adjusting weight must be checked at regular intervals within the scope of quality assurance. For this purpose, the answerable user must define a suitable interval as well as the nature and scope of this check. Information is available on KERN's home page (www.kern-sohn.com) with regard to the monitoring of balance test substances and the test weights required for this. Test weights and balances can be adjusted quickly and at a reasonable price in KERN's accredited DKD calibration laboratory (return to national normal).

3 Fundamental safety information

3.1 Observe the information in the operating instructions

Please read the operating instructions carefully before erecting and commissioning, even if you already have experience with KERN balances.

3.2 Staff training

The device may only be operated and looked after by trained members of staff.

4 Transport and storage

4.1 Acceptance check

Please check the packaging immediately upon delivery and the device during unpacking for any visible signs of external damage.

4.2 Packaging / return transport



- ⇒ Keep all parts of the original packaging for a possibly required return.
- ⇒ Only use original packaging for returning.
- ⇒ Prior to dispatch disconnect all cables and remove loose/mobile parts.
- ⇒ Reattach possibly supplied transport securing devices.
- ⇒ Secure all parts such as the glass wind screen, the weighing platform, power unit etc. against shifting and damage.

5 Unpacking, installation and commissioning

5.1 Place of installation, place of use

The balance is constructed in such a way that reliable weighing results can be achieved under normal application conditions.

By selecting the correct location for your balance, you will be able to work quickly and precisely.

Therefore please observe the following at the place of installation:

- Place the balance on a firm, level surface;
- Avoid extreme heat as well as temperature fluctuation caused by installing next to a radiator or in the direct sunlight;
- Protect the balance against direct draughts due to open windows and doors;
- Avoid jarring during weighing;
- Protect the balance against high humidity, vapours and dust;
- Do not expose the device to extreme dampness for longer periods of time. Inadmissible bedewing (condensation of air moisture on the device) can occur if a cold device is taken into a significantly warmer environment. In this case, please acclimatise the device for approx. 2 hours at room temperature after it has been disconnected from the mains.
- Avoid static charging of the material to be weighed, weighing container and windshield.

Major display deviations (incorrect weighing results) are possible if electromagnetic fields occur as well as due to static charging and instable power supply. It is then necessary to change the location.

5.2 Unpacking the Balance

Carefully remove the balance from the packaging and out of the plastic covering, then place the balance on the assigned position.

5.2.1 Installation

Install the balance in such a fashion that the weighing plate is absolutely horizontal.

5.2.2 Package volume

Serial fittings:

KERN ECB
<ul style="list-style-type: none">• Balance• Operating manual• Power adaptor

5.3 Mains supply/ Battery operation

5.3.1 Mains supply

Electric power supply is by means of the external mains supply circuit. The printed voltage level must comply with the local voltage.

Only use original KERN mains supply circuits. The use of other makes is subject to approval by Kern.

Mains adapter output voltage: 9V DC (polarity: inner terminal is negative)

5.3.2 Battery operation

Open the battery cover on the underside of the balance. Insert 6 x 1.5volt (AA) batteries.

Replace the battery cover. To preserve battery life, the balance switches off automatically after 3 minutes if no weighing has taken place.

For battery operation the balance has an automatic switchoff function which can be activated and deactivated in the menu.

When the battery power is used up the display will show "LO". Press the ON/OFF key and change the batteries at once.


When the balance is not in use for a longer period of time remove batteries and keep them separately. Leakage of battery liquid might damage the balance.

The optionally supplied battery is charged with the supplied power supply.


The battery has a service life of c. 100 hours.

The charging period for total charge is c. 10 hours.


Rechargeable Battery Installation:



1. Remove battery cover



2. Slide spacer to left or right, lever down on corner, then remove the spacer



3. Insert and connect rechargeable battery

5.4 Initial start-up

A warm-up time of 5 minutes stabilises the measured values after switching on.

The accuracy of the balance depends on the local acceleration of the fall.

Please be sure to observe the information in the chapter on adjusting.

5.5 Adjustment

As the acceleration value due to gravity is not the same at every location on earth, each balance must be coordinated – in compliance with the underlying physical weighing principle - to the existing acceleration due to gravity at its place of location (only if the balance has not already been adjusted to the location in the factory). This adjustment process must be carried out during the initial start-up, after change in location and variation of surrounding temperature. It is also recommendable to adjust the balance periodically during weighing operation in order to obtain exact measured values.

5.6 Adjusting

Using a precision weight, the accuracy of the balance can be checked at any time and adjusted.

Adjustment procedure:

Check that the surrounding conditions are stable.

A short warm-up time of about 5 minutes is recommended for stabilisation.

Operation	Display
Turn balance on using ON/OFF button	0,00
Hold down TARE button for 3 seconds The weight value for adjusting the scales will appear in the display.	10,00
Place the required adjustment weight on the weighing platform (see section 1, "Technical data") Shortly afterwards, this will appear: If adjustment has not worked correctly or if the wrong adjustment weight was used then this will be displayed: In this case switch the power off and on and repeat the adjustment process.	F E
Remove the weight from the weighing platform and the display will automatically return to normal weighing mode. Adjustment has been successfully completed.	0,00

6 Operation

6.1 Weighing

- The balance is switched on by pressing the "**ON/OFF**" key.
- The balance performs auto-diagnostics (for 2 s) and then displays "**0.00**".
- If the weighing object is heavier than the weighing range the display indicates "**E**" (=Overload).
- The balance is switched off by pressing the "**ON/OFF**" key once.

6.2 Taring (TARE key)

- Switch the balance with the "**ON/OFF**" key on and wait until display appears as "**0.00**". Position the tare load and press the "**TARE**" key.
- The balance display becomes "**0.00**".
- The item to be weighed can now be placed in the tare container and the weight can be read off.

7 Maintenance, upkeep, disposal

7.1 Cleaning

Please disconnect the device from the operating voltage before cleaning.

Only use a cloth dampened with mild suds and not aggressive cleaning agents (solvents or similar). Please ensure that fluids are not able to get into the device and rub off using a clean, soft cloth.

Loose sample residue/powder can be removed carefully using a brush or hand vacuum cleaner.

Remove any spilt material to be weighed immediately.

7.2 Maintenance, upkeep

The device may only be opened by trained service engineers authorised by KERN. Disconnect from the mains supply before opening.

7.3 Disposal

The operating company shall dispose of the packaging and the device in compliance with the valid national or regional law of the operating location.

8 Troubleshooting

The balance should be switched off for a short time following an interruption in the programme sequence and disconnected from the mains supply. It is then necessary to repeat the weighing process from the beginning.

Help:

Interruption

Possible cause

Weight display is not illuminated.

- The balance is not switched on.
- The mains supply connection has been interrupted (mains cable not plugged in/faulty).
- Power supply interrupted. .

The weight display changes continually

- Draught/air movement
- Table/floor vibrations
- The weighing plate is in contact with foreign matter.
- Electromagnetic fields / static charging (choose different location/switch off interfering device if possible)

The weighing result is obviously incorrect

- The balance display is not set to zero
- Adjustment is no longer correct.
- Great fluctuations in temperature.
- Electromagnetic fields / static charging (choose different location/switch off interfering device if possible)

Switch the balance off if other error messages should appear and then switch on again. Contact the manufacturer if the error message does not disappear.